



# Brtni prsten Roxtec ComSeal BG™

Brtna za uvođenje kabela sa stupnjem zaštite IP 55 za izjednačavanje potencijala i uzemljenje.

Roxtec ComSeal BG™ pruža stupanj zaštite IP 55 i namijenjen je za izjednačavanje potencijala i uzemljenje armiranih i metalom prevučeni kabela i cijevi. Brtna je dostupna s aluminijskim okvirom prevučeni niklom u jednoj veličini i podržava do 32 kabela. Brtni moduli Roxtec BG™ prilagođavaju se kabelima i cijevima različiti veličina te se mogu upotrebljavati za stvaranje dodatnog prostora u brtni.



- Štiti od glodavaca
- Lagano
- Površinski učinkovito
- Dopušta pred-terminirane kabele
- Osigurava rezervni prostor
- Prilagođava se kabelima i cijevima različiti veličina

## Karakteristike proizvoda



IP/UL NEMA



Električna sigurnost

## Struktura instalacije



Ormari i kućišta

## Vrsta montaže



Pričvršćivanje vijcima

## Klase i certifikati

### Nepropusnost

- IP 55 prema IEC 60529, UL/NEMA 3,12,12K

### Podržava

- Povezivanje i uzemljenje

## Dimenzije okvira

mm/kg

Varijante okvira u nastavku ograničen su izbor. Za cijeli raspon okvira i konfiguracija posjetite [roxtec.com](https://www.roxtec.com).


Proizvod	Otvori okvira	Prostor za smještaj	Vanjske dimenzije WxHxD	Dimenzije otvora w x h	Težina	Broj artikla
COMSEAL 32 BG FRAME ASSEMBLY	2	40 x 160	135 x 241 x 56	103(+1/-1) x 209(+1/-1)	1	159708

## Komponente za brtvljenje

### Komponente za brtvljenje



Mazivo Roxtec



Modul CM BG™ sa značajkom Multidiameter™

Za detaljne informacije posjetite [roxtec.com](https://www.roxtec.com).



## Unaprijed konfigurirani kompleti za prolaze

mm/kg



Proizvod	Konfiguracija	Vanjske dimenzije WxHxD	Dimenzije otvora w x h	Težina	Broj artikla
COMSEAL 32/20 BG	16x (3.5-16.5), 4x (9.5-32.5)	135 x 241 x 56	103(+1/-1) x 209(+1/-1)	1.8	196984
COMSEAL 32/8 BG	8x (9.5-32.5)	135 x 241 x 56	103(+1/-1) x 209(+1/-1)	1.8	196985
COMSEAL 32/32 BG	32x (3.5-16.5)	135 x 241 x 56	103(+1/-1) x 209(+1/-1)	1.8	196987

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on = 2025-03-12