



# Roxtec CF 16 BG-gjennomføring™

Kabelgjennomføring for jording og potensialutjevning med lavprofilramme.

Roxtec CF 16 BG™ er kabelinngangstetning med lav profil som er designet for jording og potensialutjevning av armerte og metallkleddede kabler. Gjennomføringen er tilgjengelig med en ramme i 304 rustfritt stål. Roxtec BT™-moduler er tilpassningsbare til kabler i ulike størrelser.



- Skadedyrbestandig
- Korrosjonsbestandig
- Arealeffektiv
- Godkjent for kabelavslutning
- Tilpasses kabler og rør i forskjellige størrelser.

## Produktetegenskaper



IP/UL NEMA



Elektrisk sikkerhet

## Struktur for installasjon



Kabinetter  
og  
kapslinger

## Festetype



Bolting

## Graderinger og sertifikater

### Tetthet

- IP 66/67 i henhold til IEC 60529

### Støtter

- Jording og potensialutjevning (bonding and grounding)

## Rammedimensjoner


mm/kg

Rammevariantene nedenfor er et begrenset utvalg. Du kan besøke [roxtec.com](https://www.roxtec.com) for det komplette utvalget av rammer og konfigurasjoner.

Tittel	Rammeåpninger	Fyllplass	Utvendige mål WxHxD	Utsparingsmål w x h	Vekt	Art.nr.
CF 16 BG AISI304	1	40 x 160	93 x 234 x 42	71(+1/-1) x 187(+2/-0.5)	1.4	216667

## Tetningskomponentdata


### Tetningskomponenter



RM BG™ blindmodul



smøremiddel



RM BG™-moduler med  
Multidiameter™

For ytterligere informasjon, kan du besøke [www.roxtec.com](https://www.roxtec.com).



## Forhåndskonfigurerte gjennomføringskit

mm/kg



Tittel	Konfigurasjon	Utvendige mål WxHxD	Utsparingsmål w x h	Vekt	Art.nr.
CF 16/4 BG AISI304	4x (9.5-32.5)	93 x 234 x 42	71(+1/-1) x 187(+2/-0.5)	1.4	216685
CF 16/10 BG AISI304	8x (3.5-16.5), 2x (9.5-32.5)	93 x 234 x 42	71(+1/-1) x 187(+2/-0.5)	1.4	216687
CF 16/16 BG AISI304	16x (3.5-16.5)	93 x 234 x 42	71(+1/-1) x 187(+2/-0.5)	1.4	216686

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2025-03-15