



Roxtec GH BG[™] brtva

Brtva s malom prirubnicom i vijkom za uzemljenje za pričvršćivanje na ravne površine pomoću vijaka.

Roxtec GH BG[™] brtva je za kabele i cijevi namijenjena povezivanju i uzemljenju. Pravokutni čelični okvir pričvršćuje se na čelične ili "sendvič" zidove/podove i omogućuje gusto postavljanje kabela i cijevi. Brtva može se koristiti s okvirom za proširenje GE od galvaniziranog čelika za pokrivanje dubine debelog zida.

- Štiti od glodavaca
- 🔘 Lako za održavanje i pregledavanje

Karakteristike proizvoda

IP/UL NEMA



sigurnost

Plinotjesnost

Vrsta montaže

Pričvršćivanje vijcima

Struktura instalacije

Vatrootpornost

Ormari i kućišta

Klase i certifikati

Požar

- Razred E/EI u skladu s normom EN 13501
- Razred F/T u skladu s normom UL 1479
- Nepropusnost
- Plin: 0,1 bara (katastrofalni)
- IP 66/67 prema IEC 60529

Podržava

Povezivanje i uzemljenje

Dimenzije okvira

mm/kg

w

Varijante okvira u nastavku ograničen su izbor. Za cijeli raspon okvira i konfiguracija posjetite roxtec.com.

	Proizvod	Otvori okvira	Prostor za smještaj	Vanjske dimenzije WxHxD	Dimenzije otvora w x h	Težina	Broj artikla
	GH BG 6x1 GALV	1	120 x 180	252.5 x 350 x 93.6	148(+5/-5) x 245(+5/-5)	4.4	109604
	GH BG 6x2 GALV	2	120 x 180	383 x 350 x 93.6	278(+5/-5) x 245(+5/-5)	7.5	110003
F	GH BG 6x3 GALV	3	120 x 180	513.5 x 350 x 93.6	409(+5/-5) x 245(+5/-5)	10.4	110015
	GH BG 6x1 AISI316	1	120 x 180	252.5 x 350 x 93.6	148(+5/-5) x 245(+5/-5)	4.9	122511
	GH BG 6x2 AISI316	2	120 x 180	383 x 350 x 93.6	278(+5/-5) x 245(+5/-5)	6.7	122512
	GH BG 6x3 AISI316	3	120 x 180	513.5 x 350 x 93.6	409(+5/-5) x 245(+5/-5)	9.9	110477





Komponente za brtvljenje

kompenzaciju RM BG™

Komponente za brtvljenje



Modul RM BG™ sa

značajkom Multidiameter™











dodaci ES i BG



Mazivo Roxtec

Okvir za proširenje GE Alati za pridržavanje Roxtec



Klin i komplet klinova Roxtec

Za detaljne informacije posjetite roxtec.com.

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use. Roxtec gives no guarantee for the Roxtec systems or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, accurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system was designed or intended. Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or consequential, punitive, special, exemplary or incidental damages or losses. The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from https://www.roxtec.com/ar/artis.com/article.com/article.com/article.com/article.com/article.com/article.com/article.com/article.com/article.com/article.com/article.com/article/arti

https =//www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/ We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International B and is protected by copyright. This document was generated on = 2025-07-05

