


https://www.roxtec.com/linktransit/en-sg/solution/1112




# **Roxtec RG M63 seal**

Round cable entry for standard round knock-outs.

The Roxtec RG M63 is a round entry seal for multiple cables. The transit fits standard ISO 63 knock-outs and can accommodate from 1 to 9 cables. This cable gland option is available in nickel-plated brass or 316L stainless steel.







**Product characteristics** 



IP/UL NEMA

#### Structure of installation



Cabinets & enclosures

## **Ratings & certificates**

### **Tightness**

.....

IP 66/67, UL/NEMA 4,4X,12,13

### **Sealing components**

### **Sealing components**







GM module with Multidiameter™

Lubricant

**Accessories** 



RG M63 tools

For detailed information, please visit roxtec.com.

1/2





### **Pre-configured transit kits**

#### in/lbs













RG M63/4 RG M63/1

RG M63/9

RG M63/1 AISI316L RG M63/4 AISI316L

RG M63/9 AISI316L

Product	Configuration	Aperture dimensions ∅	Weight	Art. no
RG M63/1	1x (0.374-1.280)	2.48 - 2.52	1.2	RG00063010046
RG M63/4	4x (0.138-0.650)	2.48 - 2.52	1.2	RG00063040046
RG M63/9	9x (0.138-0.413)	2.48 - 2.52	1.2	RG00063090046
RG M63/1 AISI316L	1x (0.374-1.280)	2.48 - 2.52	1.2	RG00063010021
RG M63/4 AISI316L	4x (0.138-0.650)	2.48 - 2.52	1.2	RG00063040021
RG M63/9 AISI316L	9x (0.138-0.413)	2.48 - 2.52	1.2	RG00063090021

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from https://www.roxtec.com/en/about-roxtec/aeneral-terms-of-sales/

https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/
We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2024-04-27

2/2 2024-04-27