



Passage Roxtec CF 8/32 EMC

Passage pour une forte densité de câbles, pour le blindage électromagnétique, avec un cadre en aluminium.

Les Roxtec CF 8 EMC et CF 32 EMC sont des passages de câbles étanches conçus pour maintenir les performances de blindage de l'armoire. Ils permettent de protéger les composants électroniques vulnérables des menaces électromagnétiques. Les passages sont composés de cadres en aluminium nickelé. Les modules d'étanchéité Roxtec ES pour le blindage électromagnétique sont adaptables à des câbles de différentes tailles.



- Résistant aux rongeurs
- Léger
- Surface optimisée
- Accepte des câbles pré-connectés

Caractéristiques du produit



IP/UL NEMA



Protection IEM

Structure d'installation



Armoires et coffrets

Classements et certificats

Étanchéité

- IP 66/67, UL/NEMA 4,4X,12,13

Supports

- Blindage électromagnétique
- Compensation de potentiel

Dimensions du cadre

mm/kg


Les variantes de cadre ci-dessous sont une sélection limitée. Pour voir la gamme complète de cadres et de configurations, veuillez visiter [roxtec.com](https://www.roxtec.com).

Titre	Ouvertures de cadre	Espace de remplissage	Dimensions externes WxHxD	Dimensions d'ouverture w x h	Poids	N° art.
CF 8 EMC	1	40 x 80	75 x 140 x 69	61(+0.5/-0.5) x 127(+0.5/-0.5)	0.37	ECF0000080035
CF 32 EMC	2	40 x 160	130 x 230 x 69	110(+0.5/-0.5) x 216(+0.5/-0.5)	1.2	ECF0000320035



Éléments d'étanchéité


Éléments d'étanchéité




Module de compression EMC C



Module CM ES avec Multidiameter™



Module CM PE avec Multidiameter™



Module de compensation plein CM ES



Module de compensation plein CM PE



Lubrifiant Roxtec

Pour plus d'informations, veuillez consulter [roxtec.com](https://www.roxtec.com).

Kits de passage préconfigurés

mm/kg



CF 8/8 ES



CF 8/8 PE



CF 32/32 PE



CF 32/32 ES

Titre	Configuration	Dimensions externes WxHxD	Dimensions d'ouverture w x h	Poids	N° art.
CF 8/5 ES	4x (3.5-16.5), 1x (9.5-32.5)	75 x 140 x 75	61(+0.5/-0.5) x 127(+0.5/-0.5)	1	192363
CF 32/20 ES	16x (3.5-16.5), 4x (9.5-32.5)	130 x 230 x 75	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.5	192366
CF 8/8 ES	8x (3.5-16.5)	75 x 140 x 75	61(+0.5/-0.5) x 127(+0.5/-0.5)	1	192364
CF 8/8 PE	8x (3.5-16.5)	75 x 140 x 69	61(+0.5/-0.5) x 127(+0.5/-0.5)	0.8	192369
CF 32/32 PE	32x (3.5-16.5)	130 x 230 x 69	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.5	192372
CF 32/8 ES	8x (9.5-32.5)	130 x 230 x 75	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.5	192365
CF 32/32 ES	32x (3.5-16.5)	130 x 230 x 75	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.5	192367
CF 32/8 PE	8x (9.5-32.5)	130 x 230 x 69	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.3	192370
CF 32/20 PE	16x (3.5-16.5), 4x (9.5-32.5)	130 x 230 x 69	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.3	192371
CF 8/5 PE	4x (3.5-16.5), 1x (9.5-32.5)	75 x 140 x 69	61(+0.5/-0.5) x 127(+0.5/-0.5)	0.8	192368

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2024-04-23