

Roxtec CF 8/32 BG™ 穿隔系统

用于接地的高电缆密度穿隔系统チ带有铝制框架。

Roxtec CF 8 BG™ 和 CF 32 BG™ 是用于铠装电缆和金属包覆电缆接地的电缆引入密封系统

。 这些穿隔系统带有浇铸镀镍铝框架。 Roxtec BG™ 密封模块可适配各种规格的电缆。



- 防啮齿动物
- 轻型
- 节省空间
- 允许使用预端接电缆

产品特性





IP/UL NEMA

安装结构



等级和证书

密封性

IP 66/67, UL/NEMA 4,4X,12,13

支持



连接和接地

框架尺寸

下方的不同框架只是部分选择。 要了解全部的框架和配置チ请访问 roxtec.com。

标题	框架开口	密封空间	外部尺寸 WxHxD	开孔尺寸 w×h	重量	产品编号
CF 8 BG	1	40 x 80	75 x 140 x 65	61(+0.5/-0.5) x 127(+0.5/-0.5)	0.6	103465
CF 32 BG	2	40 x 160	130 x 230 x 65	110(+0.5/-0.5) x 216(+0.5/-0.5)	1.6	102826

密封组件数据

密封组件



Multidiameter™ソ多径ゾCM BG™ 模块



CM BG™ 盲堵模块



润滑脂

如需了解详细信息チ请访问 roxtec.com。

2024-04-05



https://www.roxtec.com/linktransit/zh-cn/solution/18552



预装配的穿隔套件

mm/kg



标题	配置	外部尺寸 WxHxD	开孔尺寸 w x h	重量	产品编号
CF 32/32 BG B	32x (3.5-16.5)	130 x 230 x 65	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.5	103461
CF 32/8 BG B	8x (9.5-32.5)	130 x 230 x 65	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.6	103462
CF 32/20 BG B	4x (9.5-32.5), 16x (3.5-16.5)	130 x 230 x 65	110(+0.5/-0.5) x 216(+0.5/-0.5)	2.6	103463
CF 8/8 BG B	8x (3.5-16.5)	75 x 140 x 65	61(+0.5/-0.5) x 127(+0.5/-0.5)	0.9	103464

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential annufacturer or incidental damages or lesses.

common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/
We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2024-04-05

2/2 2024-04-05