



Etanșare Roxtec RS EMC cu SL RS

Etanșare EMC cu manșon pentru sudare, pentru cabluri sau țevi individuale.

Roxtec RS EMC cu SL RS este o etanșare ce asigură și compatibilitatea electromagnetică. Solutia are un manșon metalic și este concepută pentru treceri singulare de cabluri sau țevi. Solutia are două jumătăți cu straturi detașabile, putând fi ajustată pentru cabluri și țevi de diferite dimensiuni. Există posibilitatea de a alege între versiunea ES, pentru ecranare electromagnetică și versiunea PE, care oferă protecție împotriva interferențelor transmise. Manșonul este sudat pe structură. Utilizați stick-ul de testare Roxtec EC pentru a obține o indicație a performanței electrice a instalărilor trecerilor de cabluri cu soluțiile Roxtec BG™ sau ES.



- Rezistent la rozătoare
- Rapid și ușor de instalat

Caracteristicile produsului



Structura instalației



Metal

Tip de montaj



Sudare

Clase și certificate

Foc

- CLASA A conform Codului FTP IMO 2010
- CLASA H, conform Codului FTP IMO 2010 + curba de încărcare la incendiu HC (hidrocarburi)
- Foc cu jet, conform ISO 22899-1 și OTI 95634

Etanșeitate

- Gaz: 2,67 bari (catastrofică)
- Apă: 4 bari (catastrofică)

Suporturi


- Ecranare electromagnetică
- Egalizarea de potențial

Date componente de etanșare


Componente de etanșare



Manșon SL RS



Etanșare RS ES



Etanșare RS PE



Lubrifiant Roxtec

Accesorii



Accesorii ES și BG

Pentru mai multe informații, vă rugăm să vizitați roxtec.com.

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2024-04-09