



# Roxtec B Ex-gjennomføring

Ex-gradert gjennomføring med fleksibel ramme for forskjellige kombinasjoner.

Roxtec B Ex er en gjennomføring for flere kabler og rør klassifisert for Ex e og Ex tb-områder. Den åpningsbare metallrammen boltes sammen for å danne forskjellige størrelser og kombinasjoner, og støpes deretter inn i strukturen, enten for ettermontering rundt eksisterende kabler eller rør eller for bruk i nye konstruksjoner. Roxtec Ex-tetningsmodulene tilpasses kabler og rør av forskjellige størrelser og kan brukes til å bygge inn reservekapasitet i tetningen.



- Perfekt for ettermontering

## Produktegenskaper



Brannklassifisert



IP/UL NEMA



Ex klassifisert



EMI-beskyttelse

## Struktur for installasjon



Kabinetter og kapslinger



Metall



Betong

## Festetype



Bolting



Støping

## Graderinger og sertifikater

### Brann

- E/EI-klassifisering i henhold til EN 13501
- F/T-klassifisering i henhold til UL 1479

### Tetthet

- IP 54

### Støtter

- Potensialutjevning
- Ex klassifisert

## Rammedimensjoner

mm/kg

Rammevariantene nedenfor er et begrenset utvalg. Du kan besøke [roxtec.com](https://www.roxtec.com) for det komplette utvalget av rammer og konfigurasjoner.

Tittel	Rammeåpninger	Fyllplass	Utvendige mål WxHxD	Utsparingsmål w x h	Vekt	Art.nr.
B 6x1 B Ex GALV	1	120 x 180	200.5 x 298 x 60	146(+1/-1) x 243(+1/-1)	3.7	EXBBB0600000115
B 6x1 C Ex GALV	1	120 x 180	200.5 x 298 x 60	146(+1/-1) x 243(+1/-1)	3.6	EXBBC0600000115
B 6x2 B Ex GALV	2	120 x 180	329 x 298 x 60	274(+1/-1) x 243(+1/-1)	6.1	EXBBB0600000215
B 6x2 C Ex GALV	2	120 x 180	329 x 298 x 60	274(+1/-1) x 243(+1/-1)	5.9	EXBBC0600000215
B 6x3 B Ex GALV	3	120 x 180	457.5 x 298 x 60	403(+1/-1) x 243(+1/-1)	8.7	EXBBB0600000315
B 6x3 C Ex GALV	3	120 x 180	457.5 x 298 x 60	403(+1/-1) x 243(+1/-1)	8.6	EXBBC0600000315



# Tetningskomponentdata

## Tetningskomponenter


## Tilbehør



smøremiddel



Wedge og Wedgekit Ex



RM Ex-modul med  
Multidiameter™




RM Ex blindmodul




Stagplate Ex



holderverktøy



RM PE Ex-modul med  
Multidiameter™



RM PE Ex blindmodul



Ex-kit

For ytterligere informasjon, kan du besøke [www.roxtec.com](https://www.roxtec.com).

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2024-04-15