



Roxtec HD BG™ geçişler

Topraklama için çok sayıda kablo geçilebilen ürünler.

Roxtec HD BG™, zorlayıcı ve tehlikeli ortamlarda zırlı ve metal clad kabloların yalıtımı ve topraklaması için kullanılan kablo girişi cihazıdır. Üç farklı boyutta sunulur. Kablo geçişi açıklık başına 32 adede kadar kabloya olanak tanır. Çeşitli kablo ölçülerine uyulanabilen 316L paslanmaz çelik çerçevesi ve Roxtec BG™ yalıtım modülleri bulunur.



- Kemirgenlere dayanıklı
- Paslanmaya dayanıklı
- Hafif
- Yüzeyi verimli kullanır
- Sonlandırılmış kabloları izin verir

Ürün özellikleri



IP/UL NEMA



Elektrik güvenliği

Montaj yapılacak yapı



Panolar ve muhafazalar

Derecelendirmeler ve sertifikalar

Sızdırmazlık

- IP 66/67, UL/NEMA 4,4X,12,13

Destekler

- Topraklama

Çerçeve boyutları


mm/kg

Aşağıdaki çerçeve çeşitleri sınırlı sayıda seçenekten oluşmaktadır. Çerçeve ve yapılandırma yelpazesinin tamamı için [roxtec.com](https://www.roxtec.com) adresini ziyaret edin.


| Başlık | Çerçeve açıklıkları | Modül koyulan alan | Dış boyutlar WxHxD | Açıklık boyutları w x h | Ağırlık | Madde Numarası |
|-------------------------------|---------------------|--------------------|-----------------------|-----------------------------|---------|----------------|
| HD 16 FRAME ASSEMBLY AISI 316 | 1 | 40 x 160 | 83.8 x 236 x 60 | 64(+1/-0.5) x 216(+1/-0.5) | 1.6 | 193084 |
| HD 32 FRAME ASSEMBLY AISI316 | 2 | 40 x 160 | 130 x 236 x 60 | 110(+1/-0.5) x 216(+1/-0.5) | 2.3 | 109238 |

Yalıtım elemanı verileri

Yalıtım elemanları



MultiDiameter™ özellikli CM BG™ modülleri



CM BG™ kör modülü




Kayganlaştırıcı

Ayrıntılı bilgi için lütfen [roxtec.com](https://www.roxtec.com) adresini ziyaret edin.



Önceden yapılandırılmış geçiş kitleri

mm/kg



HD 16/4 BG



HD 16/10 BG



HD 16/16 BG



HD 32/8 BG B KIT



HD 32/32 BG B KIT



HD 32/20 BG B KIT



HDLC/24+2 BG

| Başlık | Konfigürasyon | Dış boyutlar WxHxD | Açıklık boyutları w x h | Ağırlık | Madde Numarası |
|-------------------|--------------------------------|-----------------------|-----------------------------|---------|----------------|
| HD 16/4 BG | 4x (9.5-32.5) | 83.8 x 236 x 60 | 64(+1/-0.5) x 216(+1/-0.5) | 2 | 193105 |
| HD 16/10 BG | 2x (9.5-32.5), 8x (3.5-16.5) | 83.8 x 236 x 60 | 64(+1/-0.5) x 216(+1/-0.5) | 2 | 198299 |
| HD 16/16 BG | 16x (3.5-16.5) | 83.8 x 236 x 60 | 64(+1/-0.5) x 216(+1/-0.5) | 2 | 193104 |
| HD 32/8 BG B KIT | 8x (9.5-32.5) | 130 x 236 x 60 | 110(+1/-0.5) x 216(+1/-0.5) | 3.3 | 120373 |
| HD 32/32 BG B KIT | 32x (3.5-16.5) | 130 x 236 x 60 | 110(+1/-0.5) x 216(+1/-0.5) | 3.5 | 120374 |
| HD 32/20 BG B KIT | 4x (9.5-32.5), 16x (3.5-16.5) | 130 x 236 x 60 | 110(+1/-0.5) x 216(+1/-0.5) | 3.4 | 120376 |
| HDLC/24+2 BG | 2x (24.0-54.0), 24x (3.5-16.5) | 378 x 120 x 94 | 366(+1/-1) x 108(+1/-1) | 5.6 | 173280 |

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2024-04-18