



Roxtec FlamePlus™ 穿隔系统

具有内置可敲除功能的轻型穿隔系统

Roxtec FlamePlus™ 是一种多电缆穿隔系统用于连接到不同的结构上。框架的模块化可简化处理和物流于轻型设计让它成为夹层板的理想选择于而宽法兰在螺栓和框架孔之间提供间隙于最大限度地降低连接到混凝土或砖墙上时出现裂缝的风险。内置的可敲除挡板可在施工期间和施工后提供入口保护。

这些密封模块适配各种规格的电缆于并可用于提供备用容量。



- 轻型
- 安装阶段确保密封
- 可开启式
- 模块化设计

产品特性



耐火



IP/UL NEMA

安装结构



夹芯板



混凝土

安装类型



栓接

等级和证书

火灾

- E/EI 等级符合 EN 13501

密封性

- IP 66

框架尺寸

mm/kg


下方的不同框架只是部分选择。要了解全部的框架和配置于请访问 [roxtec.com](https://www.roxtec.com)。

| 标题 | 框架开口 | 密封空间 | 外部尺寸 WxHxD | 开孔尺寸 w x h | 重量 | 产品编号 |
|-------------------------------|------|-----------|-----------------|---------------|------|--------|
| FLAMEPLUS 6x2 WITH EXT. FRAME | 2 | 120 x 180 | 487 x 433 x 310 | 351 x 297 | 8.4 | 223806 |
| FLAMEPLUS 6x3 WITH EXT. FRAME | 3 | 120 x 180 | 642 x 433 x 310 | | 11.4 | 223807 |
| FLAMEPLUS 6x1 WITH EXT. FRAME | 1 | 120 x 180 | 331 x 433 x 310 | | 5.6 | 223805 |
| FLAMEPLUS 6x1 | 1 | 120 x 180 | 332 x 433 x 67 | 196 x 297 | 2.6 | 213303 |
| FLAMEPLUS 6x2 | 2 | 120 x 180 | 487 x 433 x 67 | 351 x 297 | 5 | 213321 |
| FLAMEPLUS 6x3 | 3 | 120 x 180 | 643 x 433 x 67 | 507 x 297 | 6.4 | 213322 |
| FLAMEPLUS 6x4 | 4 | 120 x 180 | 798 x 433 x 67 | 662 x 297 | 7.5 | 235413 |



密封组件数据


密封组件



Multidiameter™ 多径 VRM 模块



密封套件



隔层板



润滑脂



楔形压紧件和楔形压紧套件

如需了解详细信息请访问 [roxtec.com](https://www.roxtec.com)。

The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2024-06-29