



Roxtec UG™-gennemføring knock-out frame

Ramme med knock-out plade til tætning før kabel- og rørføring.

Roxtec knock-out frame (KOF) UG™ er en multikabel- og rørgennemføring, der holder byggepladsen tør under og efter byggeriet. Rammen kan installeres og støbes ind i konstruktioner med forskellige tykkelser og opretholder en tæt forsegling, indtil pladen slås ud for kabel- og rørføring. Når kabler eller rør er ført, tætnes gennemføringen med Roxtec UG™-moduler til underjordisk brug. Tætningsmodulerne kan tilpasses til kabler og rør i forskellige størrelser og kan bruges til at indbygge ekstra kapacitet i gennemføringen.

KOF med plade kan også bruges til at give ekstra kapacitet til fremtidige behov. Rammens dybde er justerbar i intervaller af 50 mm ved hjælp af KOF-adapteren, så den kan tilpasses forskellige vægtykkelser. Rammerne har en integreret funktion, der gør det muligt at forbinde dem til pladsbesparende klynger.

- Letvægt
- Pladsbesparende
- Tæthed i byggefasen

Produktegenskaber



Vandtæt



Gastæt



IP/UL NEMA

Byggekonstruktion



Beton

Monteringstype



Støbning



Normeringer og certifikater

Tæthed

- Gas: 0,3 bar (konstant)
- Vand: 0,5 bar (konstant)
- IP 68

Rammedimensioner


mm/kg

De nedenstående rammevarianter udgør et begrænset udvalg. Du kan se hele udvalget af rammer og konfigurationer på [roxtec.com](https://www.roxtec.com).

Title	Rammeåbninger	Pakkeareaö	Udvendige mål WxHxD	Åbningsmål w x h	Vægt	Art.-nr.
KOF 6x1 D=100	1	120 x 180	226 x 324 x 100	187 x 285	0.6	249058

Data om tætningskomponenter

Tætningskomponenter



Stayplate



Lubrikant



RM UG™-modul med Multidiameter™



RM UG faste moduler/enkeltdiametermoduler

For merne information, besøg venligst [roxtec.com](https://www.roxtec.com).



The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2025-12-18

