



Roxtec utslagbar ramme UG™-gjennomføring

Ramme med knock-out-plate for tetting i forkant av kabel- og rørføring.

Roxtec knock-out-ramme (KOF) er en lettvektig multikabelgjennomføring beregnet for innstøping. Den holder området tørt både under og etter byggeprosessen. Rammen kan monteres og støpes inn i konstruksjoner av forskjellige tykkelser, noe som sørger for tett forsegling til platen slås ut for gjennomføring av kabler og rør. Når kabler eller rør er installert, tettes gjennomføringen med Roxtec UG™-moduler for bruk under bakkenivå. Tetningsmodulene kan tilpasses kabler og rør i forskjellige størrelser og kan brukes til å bygge inn reservekapasitet i gjennomføringen.

KOF med plate kan også brukes til reservekapasitet for fremtidige behov. Rammedybden kan justeres med 50 mm ved hjelp av KOF-adapteret, slik at den kan tilpasses forskjellige veggtykkelser. Rammene har en innebygd løsning som gjør det mulig å koble dem sammen til plassbesparende klynger.



- Lettvekt
- Arealeffektiv
- Tetthet gjennom konstruksjonsfasen

Produktegenskaper



Vannrett



Gassrett



IP/UL NEMA

Struktur for installasjon



Betong

Festetype



Støping

Graderinger og sertifikater

Tetthet

- Gass: 0,3 bar (konstant)
- Vann: 0,5 bar (konstant)
- IP 68

Rammedimensjoner


mm/kg

Rammevariantene nedenfor er et begrenset utvalg. Du kan besøke [roxtec.com](https://www.roxtec.com) for det komplette utvalget av rammer og konfigurasjoner.

Tittel	Rammeåpninger	Fyllplass	Utvendige mål WxHxD	Utsparingsmål w x h	Vekt	Art.nr.
KOF 6x1 D=100	1	120 x 180	226 x 324 x 100	187 x 285	0.6	249058

Tetningskomponentdata

Tetningskomponenter



Stagplate



smøremiddel



RM UG™-modul med Multidiameter™



RM UG-moduler med fast/enkelt diameter

For ytterligere informasjon, kan du besøke www.roxtec.com.



The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2025-12-18

