



Roxtec knock-out frame UG™-genomföring

Ram med knock-out-platta för tätning före kabel- och rördragning.

Roxtec knock-out frame (KOF) UG™ är en genomföring för flera kablar och rör som håller platsen torr under och efter byggnationen. Ramen kan installeras och gjutas in i strukturer av olika tjocklekar och upprätthåller en säker tätning tills dess platta slås ut för kabel- och rördragning. När kablar eller rör har dragits, tätas genomföringen med Roxtec UG™-moduler för användning under jord. Tätningsmodulerna kan anpassas till kablar och rör av olika storlekar och kan användas för att bygga in reservkapacitet i genomföringen.

KOF med platta kan också användas för att ge reservkapacitet för framtida behov. Ramdjupet kan justeras med 50 mm med hjälp av KOF-adaptorn, så att det passar olika väggdjup. Ramarna har en inbyggd funktion som gör att de kan sammankopplas till utrymmeseffektiva kluster.



- Låg vikt
- Utrymmeseffektiv
- Täthet under byggfasen

Produktegenskaper



Vattentät



Gastät



IP/UL NEMA

Konstruktion för installation



Betong

Monteringssätt



Gjutning

Klassningar & certifikat

Täthet

- Gas: 0,3 bar (konstant)
- Vatten: 0,5 bar (konstant)
- IP 68

Ramdimensioner


mm/kg

Ramvarianterna nedan är ett begränsat urval. Du hittar hela utbudet av ramar och konfigurationer på [roxtec.com](https://www.roxtec.com).

Titel	Ramöppningar	Packningsutrymme	Ytermått WxHxD	Öppningens mått w x h	Vikt	Art. nr
KOF 6x1 D=100	1	120 x 180	226 x 324 x 100	187 x 285	0.6	249058

Information om tätningskomponenter

Tätningskomponenter



stagbricka



smörjmedel



RM UG™-modul med Multidiameter™



RM UG solid/single diameter modules

Detaljerad information finns på [roxtec.com](https://www.roxtec.com).



The product information provided by Roxtec does not release the purchaser of the Roxtec system, or part thereof, from the obligation to independently determine the suitability of the products for the intended process, installation and/or use.

Roxtec gives no guarantee for the Roxtec system or any part thereof and assumes no liability for any loss or damage whatsoever, whether direct, indirect, consequential, loss of profit or otherwise, occurred or caused by the Roxtec systems or installations containing components not manufactured by an authorized manufacturer and/or occurred or caused by the use of the Roxtec system in a manner or for an application other than for which the Roxtec system was designed or intended.

Roxtec expressly excludes any implied warranties of merchantability and fitness for a particular purpose and all other express or implied representations and warranties provided by statute or common law. User determines suitability of the Roxtec system for intended use and assumes all risk and liability in connection therewith. In no event shall Roxtec be liable for indirect, consequential, punitive, special, exemplary or incidental damages or losses.

The Roxtec products are offered and sold in accordance with the conditions of the Roxtec General Terms of Sales. The latest version of the Roxtec General Terms of Sales can be downloaded from <https://www.roxtec.com/en/about-us/about-roxtec/general-terms-of-sales/>

We reserve the right to make changes to the product and technical information without further notice. Any errors in print or entry are no claims for indemnity. The content of this publication is the property of Roxtec International AB and is protected by copyright.

This document was generated on: 2025-12-18

